

E-NEX LEISURE Batteries



Ideal solution for Marine & RV

Dual purpose batteries are ideal for applications that require starting and deep cycle service.

They deliver powerful cranking amperage for easy starting, and low amp draw service for reliable auxiliary power.

Dual purpose batteries are a perfect compromise between the unique demands of starting service, deep cycling and low amp draw service.



ATLASBX America Corporation

📍 STE 600, 333 COMMERCE ST, NASHVILLE, TN 37201-1836

📞 Tel : 615-432-0725 ✉ E-mail : slee8012@atlasbx.co.kr 🌐 URL : www.atlasbx.com

ATLASBX™
THE POWER COMPANY

The Best Choice of Each Battery Rating Criteria

	AGM	XDC	DC	XV
Starting Service Capability	■■■■■	■■■□	■■■□	■■■□
Dual Purpose Service Capability	■■■■■	■■■□	■■■□	N/A
Deep Cycle Service Capability	■■■■■	■■■□	■□□□	N/A
Floating Service Capability	■■■■■	■■■□	■■■□	■□□□
Maintenance Free	■■■■■	■■■□	■■■□	■■■□
Storage Ability	■■■■■	■■■□	■■■□	■■■□
Spill-Proof	■ YES	□ NO	□ NO	□ NO

SPECIFICATION

Gr.No	Type No.	SAE CCA (0°F)	RC (min.)	Dimension(Inch)			Layout	Terminal	Hold-Down
				L	W	TH			
Leisure AGM Batteries									
24	AGM24-750	750	140	10 1/4	6 13/16	8 7/8	10	Marine	B1
24R	AGM24R-750	750	140	10 1/4	6 13/16	8 7/8	11	Marine	B1
C31	AGM C31-800	800	180	13	6 13/16	9 7/16	18	Threaded Post	B0
	AGM C31-950	950	200	13	6 13/16	9 7/16	18	Threaded Post	B0
Deep Cycle & Starting Batteries(XDC)									
24	XDC24-500	500	120	10 1/4	6 13/16	8 7/8	10	Marine	B1
27	XDC27-600	600	150	12 1/16	6 13/16	8 7/8	10	Marine	B1
31	XDC31-650	650	180	13	6 13/16	9 7/16	18	Marine	B0
Starting Batteries(XV)									
24	XV24-560	560	105	10 1/4	6 13/16	8 7/8	10	Marine	B1
	XV24-600	600	125	10 1/4	6 13/16	8 7/8	10	Marine	B1
	XV24-720	720	155	10 1/4	6 13/16	8 7/8	10	Marine	B1
27	XV27-720	720	155	12 1/16	6 13/16	8 7/8	10	Marine	B1
	XV27-800	800	180	12 1/16	6 13/16	8 7/8	10	SAE Post	B1
31	XV31-800	800	180	13	6 13/16	9 7/16	18	Marine	B0
Dual Purpose Batteries(DC)									
24	DC24-680	680	140	10 1/4	6 13/16	8 7/8	10	Marine	B1
27	DC27-750	750	170	12 1/16	6 13/16	8 7/8	10	Marine	B1
31	DC31-800	800	180	13	6 13/16	9 7/16	18	Marine	B0
Lawn & Garden Batteries									
U1	U1L-190	190	25	7 3/4	5 3/16	7 5/16	10	U1 LUG	
	U1L-250	250	32	7 3/4	5 3/16	7 5/16	10	U1 LUG	
	U1L-300	300	40	7 3/4	5 3/16	7 5/16	10	U1 LUG	
	U1L-340	340	48	7 3/4	5 3/16	7 5/16	10	U1 LUG	
U1R	U1R-190	190	25	7 3/4	5 3/16	7 5/16	10	U1 LUG	
	U1R-250	250	32	7 3/4	5 3/16	7 5/16	11	U1 LUG	
	U1R-300	300	40	7 3/4	5 3/16	7 5/16	11	U1 LUG	
	U1R-340	340	48	7 3/4	5 3/16	7 5/16	10	U1 LUG	

Layout

10		11		18		19	
11F		17		24		26	